
Wendt X5 • 5-Channel Mixer

5 Channels - 4 Outputs (5 x 2 x 2)



© 2001 Wendt Inc., Westlake Village, CA, USA

Features & Technical Specifications

5 Channels - Including Channel 1 & 2 stereo (switchable)

PFL (PreFade Listen) - 5 Channels, push button momentary

Line Out (B) - XLR R/L, balanced, mic/line switchable

Line Out (A) - TA3 R/L, balanced, mic/line switchable, also R+L or stereo

Returns - Multiple returns (front panel switchable) A & B, 3.5mm mini jack

Power - Internal (8 AA alkaline batteries, 12-15 hours), or external 9-18 v, 4-pin Hirose conn.

Link - Allows two X5 mixers to be cross-linked, (10 channel mix, plus 8 outputs), TA5 conn.

Mic Powering - 48PH, DYN, 12T

Tone Oscillator - 400 Hz, 0db VU or 0dbu for PPM version

Low-Cut Filter - 10 Hz, 140 Hz, 12db/octave

Frequency Response - 20 Hz to 20 KHz

Distortion & Noise - Less than 0.1% THD and EIN -128dbV

Size & Weight - 11.28" x 7.4" x 1.85" (286mm x 188mm x 47mm), weight = 3.5 lbs. including batteries and bag (uses Wendt X4 bag)

Other Features - Limiter; PAN switches (front panel); slate mic; one phone jack (1/4 in.); mono or stereo headphone; MS tape return, multi-pin ENG cable port (X4 snake cable compatible); stereo mic out - unbalanced, 3.5mm; metering - VU and optional PPM.

Custom bag with padded shoulder strap included



Wendt Inc.

Westlake Village, CA • USA • Tel: 805 494-4432

www.wendtaudio.com • www.wendtinc.net • www.wendtmixers.com

E-mail: wendt_inc@earthlink.net

Front Panel



Left Side Panel



Right Side Panel

Bottom Panel

